voltages to each logic gate location, analogous to transistors within a classical computer processor. Only a handful of global radiation fields, which are broadcasted across the entire quantum computer architecture, are required, no matter how many ions are used as part of the quantum computation. While there are still laser beams required for laser cooling, photoionization, repumping, and sympathetic cooling, these can be applied as global beams, so their number is not strongly correlated to the number of qubits and alignment and stability requirements are not very stringent. Besides describing the method, we have also reported the experimental demonstration of the key ingredient for this approach, namely, a new type of two-qubit entanglement gate utilizing long-wavelength radiation. Using this method we have created a maximally entangled state with fidelity close to the relevant fault-tolerant threshold. This method of creating high-fidelity entangled states may also have significant impact in areas other than quantum computing, owing to its simplicity and robustness. This simple-to-implement gate mechanism can be used in a large breadth of experiments in areas relying on the creation of entanglement such as quantum simulation, quantum sensing, and quantum metrology.

We thank Klaus Mølmer for helpful discussions and Eamon Standing for performing relevant magnetic field simulations. This work is supported by the U.K.

used, and therefore the crosstalk values for the dressing fields are $C_{12} = C_{21} = 5{:}2 \quad 10^{7}$. For the rf fields used to drive the two-qubit gate, the crosstalk values would be $C_{12} = C_{21} = 2{:}0 \quad 10^{4}$ for square pulse shapes, however, the field amplitudes would be shaped with a $\sin^2$ profile as demonstrated in this work. Shaping the pulse amplitudes further reduces the crosstalk by several orders of magnitude. To see this, a numerical simulation of a two-level system driven by a field with Rabi frequency (t) and detuning was performed. The Rabi frequency was varied in time starting with a $\sin^2$ shape ramp from = 0 to = $_{max}$ for a time t_w, followed by a hold at $_{max}$ for a time t_h, and finally a second $\sin^2$ shape ramp down to = 0 in time t_w. It was found that for > 10 $_{max}$ and t_w > = $_{max}$, the error is reduced to < 10^{7}. This detuning requirement is fulfilled for both the rf and microwave dressing fields in this example. Therefore the crosstalk between ions in a single zone is < 10^{6}, and is therefore negligible compared to other error sources.

As mentioned, individual addressing of ions in different zones is achieved by positioning the ions in different zones in a different local static magnetic offset field achieved making use of the position dependent magnetic field originating from the local static magnetic field gradient within each zone. Ions that are not being addressed sit at magnetic field B_1 corresponding to position z_1, while ions that require to be addressed are moved to position z_2 resulting in a magnetic field B_2. As an example, if $B_2 \quad B_1 = 2$ G, the Zeeman states of the ions that are not being addressed are 2.8 MHz off-resonant. The crosstalk for such a frequency separation with the parameters in the example case is $6{:}4 \quad 10^{6}$ for the microwave dresse1 the crosstalk by sevt